

E39862 - 9" Digit Single Sided Race Clock

E39864 - 9" Digit Double Sided Race Clock

The race clocks can be set to display
Hours/Minutes/Seconds or
Minutes/Seconds/Hundredths of Seconds. The
race clocks can be set to count up or down.

Each race clock includes a tripod, remote, 18 AC
power cord, 10' DC power cord, and 50' computer
hook up cord.

Case Controls

Power ON/OFF switch
UP/DOWN selection switch
Show 1/100 seconds switch
Start button
Stop button
Reset button
Hours +1 button
Minutes +1 button
Seconds +1 button
Remote keypad Learning switch

Resetting the race clock:

UP mode - The clock will reset to 00:00:00
DOWN mode - The clock will reset to the original
time

How to assign remote keypad to race clock:

Press the LEARN button for 0.5 seconds and release. The display will show LEARN and flash for about 15 seconds. During this time, press #1 on the remote keypad twice. After the display has stopped flashing you may use the new remote keypad. You can assign up to 8 remote keypads to a race clock.

To clear the memory race clock's memory of remote keypads, press and hold the LEARN button for more than 20 seconds. After the display stops flashing, turn the race clock off and then back on again. Now no remote keypads will work for this race clock. You will have to reassign remote keypads following the procedure above.

Race clock is compatible with FinishLynx.



Accessories:

E39855 - Replacement Tripod
E39856 - Replacement Remote
E39858 - Carrying Case for 9" Race Clocks
REPL39100 - Replacement 9-Pin to Barrell Data Cable



www.gillathletics.com
800-637-3090

E39862 & E39864 RACE CLOCKS CUSTOMER INSTRUCTIONS

H+1: Set Hour +1

M+1: Set Minute +1

S+1: Set Second +1

DOWN PRE-SET:

Set time to 1:00 or 1:30 or 2:00 or 5:00
or 99:59:59 for count down.

START: Start counting

STOP: Stop counting

RESET: 0:00 when count up

To start value when count down

UP 0:00:01:

Always start from 0:00:00 to 0:00:01

SEC: to show resolution in seconds.

1S/100: to show 1/10 & 1/100 seconds

UP: Change to count up display

DOWN: Change to count down display

Numerical buttons 1~9 . 0: reserved

BRT: Set brightness

